

# Automotive Audio Bus A<sup>2</sup>B Transceiver

## **Data Sheet**

## AD2426W/AD2427W/AD2428W

### A<sup>2</sup>B BUS FEATURES

#### Line topology

Single master, multiple slave Up to 15 m between nodes and up to 40 m overall cable length Communication over distance Synchronous data Multichannel I<sup>2</sup>S/TDM to I<sup>2</sup>S/TDM Clock synchronous, phase aligned in all nodes Low latency slave to slave communication Control and status information I<sup>2</sup>C to I<sup>2</sup>C GPIO over distance Bus power or local power slave nodes Configurable with SigmaStudio graphical software tool

Qualified for automotive applications

### **A<sup>2</sup>B TRANSCEIVER FEATURES**

Configurable as A<sup>2</sup>B bus master or slave (AD2428W) I<sup>2</sup>C interface 8-bit to 32-bit multichannel I<sup>2</sup>S/TDM interface I<sup>2</sup>S/TDM/PDM programmable data rate Up to 32 upstream and 32 downstream channels PDM inputs for 4 high dynamic range microphones on masters or slaves Support for receiving I<sup>2</sup>S data on nodes with up to 4 PDM microphones Unique ID register for each transceiver Support for crossover or straight-through cabling Programmable settings to optimize EMC performance

### **APPLICATIONS**

Automotive audio communication link

Active noise cancellation

Microphone arrays for hands free and in car communication



Figure 1. Functional Block Diagram

A<sup>2</sup>B and the A<sup>2</sup>B logo are registered trademarks of Analog Devices, Inc.

#### Rev. Sp0

#### **Document Feedback**

Information furnished by Analog Devices is believed to be accurate and reliable. However, no responsibility is assumed by Analog Devices for its use, nor for any infringements of patents or other rights of third parties that may result from its use. Specifications subject to change without notice. No license is granted by implication or otherwise under any patent or patent rights of Analog Devices. Trademarks and registered trademarks are the property of their respective owners.

### **GENERAL DESCRIPTION**

The Automotive Audio Bus  $(A^2B^{\textcircled{s}})$  provides a multichannel, I<sup>2</sup>S/TDM link over distances of up to 15 m between nodes. It embeds bidirectional synchronous pulse-code modulation (PCM) data (for example, digital audio), clock, and synchronization signals onto a single differential wire pair. A<sup>2</sup>B supports a direct point to point connection and allows multiple, daisy-chained nodes at different locations to contribute and/or consume time division multiplexed channel content.

 $A^2B$  is a single-master, multiple-slave system where the transceiver chip at the host controller is the master. The master generates clock, synchronization, and framing for all slave nodes. The master  $A^2B$  chip is programmable over a control bus ( $I^2C$ ) for configuration and read back. An extension of this control bus is embedded in the  $A^2B$  data stream, which grants direct access of registers and status information on slave transceivers as well as  $I^2C$  to  $I^2C$  communication over distance.

The transceiver can connect directly to general-purpose digital signal processors (DSPs), field-programmable gate arrays (FPGAs), application specific integrated circuits (ASICs), microphones, analog-to-digital converters (ADCs), digital-to-analog converters (DACs), and codecs through a multichannel I<sup>2</sup>S/TDM interface. It also provides a PDM interface for direct connection of up to four PDM digital microphones.

Finally, the transceiver also supports an A<sup>2</sup>B bus powering feature, where the master node supplies voltage and current to the slave nodes over the same daisy-chained, twisted pair wire cable as used for the communication link.

Complete technical specifications are available for the A<sup>2</sup>B transceiver. Contact your nearest Analog Devices sales office to complete the nondisclosure agreement (NDA) required to receive additional product information.

Table 1.	Product	Comparison	Guide
----------	---------	------------	-------

Feature	AD2426W	AD2427W	AD2428W
Master capable	No	No	Yes
Functional TRX blocks	A only	A + B	A + B
I <sup>2</sup> S/TDM support	No	No	Yes
PDM microphone inputs	4 mics	4 mics	4 mics
Max node to node cable length	15 m	15 m	15 m

I<sup>2</sup>C refers to a communications protocol originally developed by Philips Semiconductors (now NXP Semiconductors).

©2018 Analog Devices, Inc. All rights reserved. Trademarks and registered trademarks are the property of their respective owners. D16813F-0-5/18(Sp0)



www.analog.com

## **Mouser Electronics**

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Analog Devices Inc.:

AD2428WCCSZ AD2428WCCSZ-RL AD2426WCCSZ AD2426WCCSZ-RL AD2427WCCSZ AD2427WCCSZ-RL AD2420BCPZ AD2420WCCPZ01 AD2420WCCPZ01-RL AD2426BCPZ AD2427BCPZ AD2428BCPZ AD2429BCPZ AD2429WCCPZ01 AD2429WCCPZ01-RL AD2426WCCSZ01 AD2426WCCSZ01-RL AD2427WCCSZ01 AD2427WCCSZ01-RL AD2428WCCSZ01 AD2428WCCSZ01-RL AD2420KCPZ AD2426KCPZ AD2427KCPZ AD2428KCPZ AD2429KCPZ