



**BC847BS** 

#### **DUAL NPN SMALL SIGNAL SURFACE MOUNT TRANSISTOR**

#### **Features**

- BV<sub>CEO</sub> >45V
- Ultra-Small Surface Mount Package
- Ideally Suited for Automated Insertion
- For switching and AF Amplifier Application
- Totally Lead-Free & Fully RoHS compliant (Notes 1 & 2)
- Halogen and Antimony Free. "Green" Device (Note 3)
- Qualified to AEC-Q101 Standards for High Reliability
- PPAP Capable (Note 4)


### **Mechanical Data**

- Case: SOT363
- Case Material: Molded Plastic, "Green" Molding Compound.
   UL Flammability Classification Rating 94V-0
- Moisture Sensitivity: Level 1 per J-STD-020
- Terminals: Finish—Matte Tin Finish. Solderable per MIL-STD-202, Method 208 (3)
- Weight: 0.006 grams (Approximate)

**SOT363** 



Top View



Device Schematic Top View

#### Ordering Information (Notes 4 & 5)


Part Number	Compliance	Marking	Reel Size (inches)	Tape Width (mm)	Quantity per Reel
BC847BS-7-F	AEC-Q101	K1F	7	8	3000
BC847BSQ-7-F	Automotive	K1F	7	8	3000
BC847BS-13-F	AEC-Q101	K1F	13	8	10,000

Notes:

- 1. No purposely added lead. Fully EU Directive 2002/95/EC (RoHS), 2011/65/EU (RoHS 2) & 2015/863/EU (RoHS 3) compliant.
- 2. See https://www.diodes.com/quality/lead-free/ for more information about Diodes Incorporated's definitions of Halogen- and Antimony-free, "Green" and Lead-free.
- 3. Halogen- and Antimony-free "Green" products are defined as those which contain <900ppm bromine, <900ppm chlorine (<1500ppm total Br + Cl) and <1000ppm antimony compounds.
- 4. Automotive products are AEC-Q101 qualified and are PPAP capable. Automotive, AEC-Q101 and standard products are electrically and thermally the same, except where specified. For more information, please refer to https://www.diodes.com/quality/5. For packaging details, go to our website at http://www.diodes.com/products/packages.html.

### **Marking Information**

SOT363



K1F = Product Type Marking Code YM = Date Code Marking Y = Year (ex: F = 2018) M = Month (ex: 9 = September)

Date Code Kev

Date Code Ite	"											
Year	2018	2019	20	020	2021	2022	2	2023	2024	202	25	2026
Code	F	G		Н	[	J		K	L	N	1	N
Month	Jan	Feb	Mar	Apr	May	Jun	Jul	Aug	Sep	Oct	Nov	Dec
Code	1	2	3	4	5	6	7	8	9	0	N	D



### Absolute Maximum Ratings (@TA = +25°C unless otherwise specified.)

Characteristic	Symbol	Value	Unit
Collector-Base Voltage	V <sub>CBO</sub>	50	V
Collector-Emitter Voltage	V <sub>CEO</sub>	45	V
Emitter-Base Voltage	V <sub>EBO</sub>	6	V
Collector Current	I <sub>C</sub>	100	mA
Peak Collector Current	I <sub>CM</sub>	200	mA
Peak Base Current	I <sub>BM</sub>	200	mA

# Thermal Characteristics ( $@T_A = +25^{\circ}C$ unless otherwise specified.)

Characteristic	Symbol	Value	Unit	
Power Dissipation (Note 6)	$P_{D}$	200	mW	
Thermal Resistance, Junction to Ambient (Note 6)	R <sub>OJA</sub>	625	°C/W	
Operating and Storage Temperature Range	T <sub>J</sub> , T <sub>STG</sub>	-65 to +150	°C	

# Electrical Characteristics (@T<sub>A</sub> = +25°C unless otherwise specified.)

Characteristic (Note 7)	Symbol	Min	Тур	Max	Unit	Test Condition
Collector-Base Breakdown Voltage		50	_	_	V	$I_C = 100\mu A, I_B = 0$
Collector-Emitter Breakdown Voltage	BV <sub>CEO</sub>	45	_	_	V	$I_C = 10 \text{mA}, I_B = 0$
Emitter-Base Breakdown Voltage	BV <sub>EBO</sub>	6		_	V	$I_E = 100 \mu A, I_C = 0$
DC Current Gain	h <sub>FE</sub>	200		450	_	$V_{CE} = 5.0V, I_{C} = 2.0mA$
Collector-Emitter Saturation Voltage	V <sub>CE(sat)</sub>	_		100 400	mV	$I_C = 10mA, I_B = 0.5mA$ $I_C = 100mA, I_B = 5.0mA$
Base-Emitter Saturation Voltage	V <sub>BE(sat)</sub>	ı	755	_	mV	$I_C = 10 \text{mA}, I_B = 0.5 \text{mA}$
Base-Emitter Voltage	V <sub>BE(on)</sub>	580	665	700	mV	$V_{CE} = 5.0V, I_{C} = 2.0mA$
Collector-Cutoff Current	I <sub>CBO</sub>			20 5.0	nΑ μΑ	V <sub>CB</sub> = 40V V <sub>CB</sub> = 40V, T <sub>A</sub> = +125°C
Emitter-Cutoff Current	I <sub>EBO</sub>	_	_	100	nA	$V_{EB} = 5.0V, I_{C} = 0$
Gain Bandwidth Product	f <sub>T</sub>	100		_	MHz	$V_{CE} = 5.0V, I_{C} = 10mA,$ f = 100MHz
Collector-Base Capacitance	C <sub>CBO</sub>		2.0	3.0	pF	$V_{CB} = 10V, f = 1.0MHz$
Emitter-Base Capacitance	C <sub>EBO</sub>	_	11	_	pF	V <sub>EB</sub> = 0.5V, f = 1.0MHz


Notes:


<sup>6.</sup> For the device mounted on minimum recommended pad layout FR4 PCB with high coverage of single sided 1oz copper, in still air conditions; the device is measured when operating in a steady-state condition.

7. Short duration pulse test used to minimize self-heating effect.




### Typical Electrical Characteristics (@TA = +25°C unless otherwise specified.)





vs. Collector Current







Figure 4 Typical Gain-Bandwidth Product vs. Collector Current




### **Package Outline Dimensions**

Please see http://www.diodes.com/package-outlines.html for the latest version.








SOT363							
Dim	Min	Max	Тур				
<b>A</b> 1	0.00	0.10	0.05				
A2	0.90	1.00	0.95				
b	0.10	0.30	0.25				
С	0.10	0.22	0.11				
D	1.80	2.20	2.15				
Е	2.00	2.20	2.10				
E1	1.15	1.35	1.30				
е	0.650 BSC						
F	0.40	0.45	0.425				
L	0.25	0.40	0.30				
а	0°	8°					
All Dimensions in mm							

# **Suggested Pad Layout**

 $Please see \ http://www.diodes.com/package-outlines.html \ for \ the \ latest \ version.$ 

#### **SOT363**



Dimensions	Value		
Dilliensions	(in mm)		
С	0.650		
G	1.300		
Х	0.420		
Υ	0.600		
Y1	2.500		



#### **IMPORTANT NOTICE**

DIODES INCORPORATED MAKES NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARDS TO THIS DOCUMENT, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE (AND THEIR EQUIVALENTS UNDER THE LAWS OF ANY JURISDICTION).

Diodes Incorporated and its subsidiaries reserve the right to make modifications, enhancements, improvements, corrections or other changes without further notice to this document and any product described herein. Diodes Incorporated does not assume any liability arising out of the application or use of this document or any product described herein; neither does Diodes Incorporated convey any license under its patent or trademark rights, nor the rights of others. Any Customer or user of this document or products described herein in such applications shall assume all risks of such use and will agree to hold Diodes Incorporated and all the companies whose products are represented on Diodes Incorporated website, harmless against all damages.

Diodes Incorporated does not warrant or accept any liability whatsoever in respect of any products purchased through unauthorized sales channel. Should Customers purchase or use Diodes Incorporated products for any unintended or unauthorized application, Customers shall indemnify and hold Diodes Incorporated and its representatives harmless against all claims, damages, expenses, and attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized application.

Products described herein may be covered by one or more United States, international or foreign patents pending. Product names and markings noted herein may also be covered by one or more United States, international or foreign trademarks.

This document is written in English but may be translated into multiple languages for reference. Only the English version of this document is the final and determinative format released by Diodes Incorporated.

#### LIFE SUPPORT

Diodes Incorporated products are specifically not authorized for use as critical components in life support devices or systems without the express written approval of the Chief Executive Officer of Diodes Incorporated. As used herein:

- A. Life support devices or systems are devices or systems which:
  - 1. are intended to implant into the body, or
  - 2. support or sustain life and whose failure to perform when properly used in accordance with instructions for use provided in the labeling can be reasonably expected to result in significant injury to the user.
- B. A critical component is any component in a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or to affect its safety or effectiveness.

Customers represent that they have all necessary expertise in the safety and regulatory ramifications of their life support devices or systems, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of Diodes Incorporated products in such safety-critical, life support devices or systems, notwithstanding any devices- or systems-related information or support that may be provided by Diodes Incorporated. Further, Customers must fully indemnify Diodes Incorporated and its representatives against any damages arising out of the use of Diodes Incorporated products in such safety-critical, life support devices or systems.

Copyright © 2018, Diodes Incorporated

www.diodes.com

# **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Diodes Incorporated:
BC847BS-7-F